



**Buzzer is integrated
into the base**

Provide better signal
visibility and ensure
safety awareness

**Multicolour
(3 or 7 colours)**

Easy installation and
economical

**Simple and
elegant design**

Matches various
machines

IP 65

Ideal for industrial
environments





Multicolour Beacon 240

With its new 240 series LED Installation Beacon Multicolour, WERMA now offers a compact signal device with up to seven colours in a single beacon: red, yellow, green, white, blue, violet and turquoise. A tricolor version is available as an alternative, combining the most common colours, red, yellow and green in just the one beacon. The beacon can be actuated via either a simple cable connection or a pre-assembled M12 plug – for plug & play. This allows you to signal several different statuses with just one device! The beacon can also be supplied with an attention-grabbing buzzer.



Technical Specifications


Dimensions (Ø x H)	55 mm x 46 mm (Protrusion from panel)
Housing	PC/ABS-Blend, black
Lens	PC, transparent
Fixing	Installation mounting M30
Colour options	Red, yellow, green, white, blue, violet, turquoise (RGB) Red, yellow, green (RGY)
Light effect	Permanent or Blinking Light (1 Hz frequency)
Tone types and frequency	Pulse tone, 3400 Hz
Life duration light	Up to 50,000 hrs
Life duration buzzer	Up to 5,000 hrs



LED Installation Beacon (M30) without Buzzer

	Voltage	Current consumption	Plug M12	Cable
Tricolour (RGY)	24 V DC	45 mA	240 220 55	240 210 55
Multicolour (RGB)	10-30 V DC	60 mA	240 120 50	240 110 50

240 220 55



240 120 50



240 210 55



240 110 50



LED Installation Beacon (M30) with Buzzer

	Voltage	Current consumption	Plug M12	Cable
Tricolour (RGY)	24 V DC	45 mA	240 240 55	240 230 55
Multicolour (RGB)	10-30 V DC	80 mA	240 140 50	240 130 50

240 240 55



240 140 50



240 230 55



240 130 50



WERMA Signaltechnik GmbH + Co. KG
Dürbheimerstr. 15
78604 Rietheim-Weilheim
Tel. +49 7424 9557 0
info@werma.com
www.werma.com